DCN-WCH05 Charger for 5 Battery Packs

www.boschsecurity.com





- Simultaneous charging of up to 5 battery packs
- Recharges from empty in 3 hours
- Loop-through mains connector
- ▶ Auto-ranging PSU, 100 240 VAC

This unit can simultaneously re-charge up to 5 DCN-WLIION battery packs. The charging status of each pack is shown on individual charge capacity indicator LEDs.

The unit is suitable for tabletop use, or can be wallmounted.

The loop-through mains voltage connector allows a maximum number of charging units to be connected in series to share from the same mains outlet:

• A maximum 5 chargers can be connected in series for 100 - 127 VAC, 50 - 60 Hertz regions

A maximum 10 chargers can be connected in series for 220 - 240 VAC, 50 - 60 Hertz regions.

Functions

Controls and Indicators

- Charge capacity indicator LEDs on each bin
- Mains power indicator LED

Interconnections

Mains supply connector

Loop-through mains connector

Battery pack charging connector

Technical specifications

Electrical

Supply Voltage	100 - 240 VAC +/- 10 % 50 - 60 Hz
Maximum power consumption	190 W

Mechanical

Dimensions (H x W x D)	340 x 195 x 82 mm (13.4 x 7.6 x 3.2 in)
Weight (without batteries)	1.4 kg (3.08 lb)
Color	Charcoal (PH 10736)

Ordering information

DCN-WCH05 Charger for 5 Battery Packs

charcoal color, re-charge up to 5 DCN-WLIION battery packs

Order number DCN-WCH05

DCN-WCH05-JP Charger for 5 Battery Packs (JP) Japanese version Order number DCN-WCH05-JP DCN-WCH05-US Charger for 5 Battery Packs (US) US version Order number DCN-WCH05-US

For more information, please visit http://iprobesolutions.com/conference-systems/dicentis-wireless-conference-system

Contact:

iProbe Multilingual Solutions, Inc. 419 Park Avenue South, New York, NY 10016 Tel. +1-212-489-6035 Email: info@iprobesolutions.com iprobesolutions.com



iProbe is a authorized dealer for Bosch Security Systems, Inc. Specialties include conferencing and language distribution systems.

Represented by:

Americas:

Bosch Security Systems, Inc. 12000 Portland Avenue South Burnsville MN 55337, USA Phone: +1-800-392-3497 Fax: +1-800-955-6831 audiosupport@us.bosch.com www.boschsecurity.com

Europe, Middle East, Africa: Bosch Security Systems B.V. P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Asia-Pacific: Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2699 apr.securitysystems@bosch.com www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd. Robert Bosch Ltda Security Systems Division 201 Building, No. 333 Fuquan Road Via Anhanguera, Km 98 North IBP CEP 13065-900 Changning District, Shanghai 200335 China Phone +86 21 22181111 Fax: +86 21 22182398 www.boschsecurity.com.cn

America Latina:

Campinas, Sao Paulo, Brazil Phone: +55 19 2103 2860 Fax: +55 19 2103 2862 al.securitysystems@bosch.com www.boschsecurity.com

© Bosch Security Systems 2013 | Data subject to change without notice 1827808267 | en, V5, 03. Jun 2013